

Supplement #28

84 Elm Street • Peterborough, NH 03458 USA
TEL (010)1-603-924-8818 • FAX (010)1-603-924-6348
Website: <http://www.softlanding.com> Email: techsupport@softlanding.com

TURNOVER® FOR ISERIES V100 COMMANDS

This document describes two kinds of TURNOVER® for iSeries v100 commands: TURNOVER® for iSeries v100 Main Menu and submenu commands, as well as commands that are not associated with any TURNOVER® for iSeries v100 user interface. You should run some of these commands from a command line and some as PDM user-defined options. PDM commands are clearly identified in this document.

TURNOVER® FOR ISERIES V100 MAIN MENU OPTIONS

As an alternative to using the TURNOVER® for iSeries v100 Main Menu, you can call menu options directly with commands, or you can set them up as options in **SoftMenu** (or in menus you create).

Note: You need to be authorized to run these commands. For more information, see *Chapter 3: Authorizing Users to TURNOVER® for iSeries v100* in the *TURNOVER® for iSeries v100 User Guide*.

- 1 Work with application definitions
TURNOVER OPT(1)
- 2 Maintain programmer information
TURNOVER OPT(2)
- 3 View Users authority
TURNOVER OPT(3)
- 4 Work with object history
TURNOVER OPT(4)
- 5 Check-out/check-in menu
TURNOVER OPT(5)
- 6 Work with forms
TURNOVER OPT(6)

TURNOVER® for iSeries v100 Commands

7 Submit a form to run

TURNOVER OPT(7)

8 Utility menu

TURNOVER OPT(8)

9 Work with Projects and Tasks

TURNOVER OPT(9)

10 Reporting menu

TURNOVER OPT(10)

11 Distribution menu

TURNOVER OPT(11)

12 User-defined option

(depends on contents of data area SOFTTURND/CASECMD)

set to **STRPWM** when shipped

TURNOVER® FOR ISERIES V100 SUBMENUS

Checkout/Check-in Menu

- 1 View checked out objects/members
DSPCHKOUT
- 2 Check-in by object
CHKINOBJ
- 3 Check-in by member
CHKINMBR
- 4 Checkout
CHECKOUT
- 10 View checked out IFS objects
no command
- 11 Check-in IFS object
TCHKINIFS
- 12 Checkout IFS object
TCHKOUTIFS
- 20 Work with object references
WRKOBJREF
- 21 Work with user-defined references
WRKUSRREF
- 22 Programmer Worklist Manager
STRPWM
- 30 Work with *DATA definitions
WRKTODATA

31 Checkout S/36 Menu

CHKOUTMEN

32 Checkout S/36 DFU

CHKOUTDFU

Utility Menu

- 1 Submit file purge
 PURFOR
- 2 Work with source archive files
 SAVARCS
- 4 Work with type code definitions
 WRKTOTYP
- 5 Set global defaults
 SETGLOBE
- 6 Display current release level
 DSPRELTO
- 7 Work with exits
 WRKTOEXIT
- 8 Submit reorganize of files
 RGZTOFILES
- 9 Submit save of archived objects
 SAVARCO
- 10 Lookup archived objects
 no command
- 11 Set source compare defaults
 no command
- 12 Global Programmer Worklist session defaults
 no command
- 13 Work with type code conversion table
 TCVTOBJTYP
- 14 Submit IFS archive save
 TSAVIFSARC

Reporting Menu

- 1 Print application definition
LISTDFTS
- 2 Check application definition
CHKAPPDEFN
- 3 Audit report
AUDITRPT
- 4 Audit adjustments and report
AUDITADJ
- 10 Projects and tasks
PRJTSKRPT
- 11 Resource time report
PRJRSRTIM
- 12 Project timesheet report
TIMERPT
- 13 Projects and tasks by priority
PRJPTYRPT
- 14 Project cost report
PRJCTRPT
- 15 Task aging report
TSKAGERPT
- 16 Project definition report
PRJDEFRPT
- 20 List Forms
LISTFORMS

- 21 Object history
RPTOBJHST
- 22 Programmer history
RPTPGMRHST
- 23 Source checkout history
RPTSRCUSE
- 24 Reference activity report
REFACTRPT
- 25 Related application conflict report
TRPTCON
- 30 Form distribution report
RPTFORMDST
- 31 Object distribution report
RPTOBJDST
- 40 List authorized users
LISTUSERS
- 41 Programmer profile information
LISTPGMRS

Distribution Menu

- 1 Maintain system definitions
WRKDSTSYS
- 2 Distribute form
DSTFOR
- 3 Receive Distribution
RCVFOR
- 4 Work with form log
WRKFORMLOG
- 5 Work with remote application definitions
WRKRMTAPP
- 6 Override network distribution method
TCFGNETDST
- 7 Remote Configuration Wizard
TRMTCFGWIZ

ADDITIONAL MENU COMMANDS

Access Helpdesk Requester panel

HELPDESK

Access Helpdesk request entry panel

FASTTASK

Access work task coordinator's review panel

WORKTASK

Access Wisedesk help trees

WRKHLPTREE

TURNOVER® FOR ISERIES V100 COMMANDS

On the following pages, the TURNOVER® for iSeries v100 commands that are listed (and not all commands are listed) are in alphabetic order. Some commands are considered application program interfaces (APIs) and are discussed in their respective online Help. Fields are also described in the online Help.

UNICOM Systems, Inc. Note

For many of the panels shown in this document, additional parameters will appear if you press **F10**. The panels in this document show all parameters, including the additional parameters.

ADDCATSTR Add Category Search String

This command is used to add search strings to a category or subcategory’s task selection criteria. This is the same as using option **1=Add** on the *Work with Category Search Strings* panel. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```

                                Add Category Search String (ADDCATSTR)

Type choices, press Enter.

Tree . . . . . _____ Name
Path . . . . . _____
_____
_____
Search String . . . . . _____
Sequence . . . . . *NEXT          Number, *NEXT
Scope of search . . . . . *BOTH          *BOTH, *DESC, *DTLS
Case sensitive search . . . . . *NO          *YES, *NO

                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
    
```

ADDHLPCAT Add Help Tree Category

This command is used from the command line to add a category or subcategory to a help tree. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```

                                Add Help Tree Category (ADDHLPCAT)

Type choices, press Enter.

Tree . . . . . _____ Name
Path of Parent Category . . . . . _____
_____
_____
New Category . . . . . _____ Name
Description . . . . . _____
Search Strings . . . . . _____
+ for more values
Submit build . . . . . *YES          *YES, *NO

                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F10=Additional parameters   F12=Cancel
F13=How to use this display   F24=More keys
    
```

TURNOVER® for iSeries v100 Commands

ADDHLPTREE Add Help Tree

This command is executed when you use option **1** on the *Work with Help Trees* panel, to create a new help tree on your system. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```

                                Add Help Tree (ADDHLPTREE)

Type choices, press Enter.

Help tree . . . . . > _____ Name
Description . . . . . _____
_____

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

ADDPWLITM Add Programmer Worklist Item

Add an item (object or source member name) to a programmer's worklist during the preliminary stages of a project task.

```

                                Add Programmer Worklist Item (ADDPWLITM)

Type choices, press Enter.

List . . . . . *SELECT _____ Name, *SELECT, *ACTIVE
Object . . . . . _____ Character value, *FORM
Attribute . . . . . _____ *SELECT, *ALL, AAUDIT, ABPG.
Checkout item . . . . . *NO _____ *NO, *YES
Description . . . . . *OBJD _____

Programmer . . . . . *LIST _____ Name, *LIST
Reference . . . . . *LIST _____ *LIST, Char
User defined status . . . . . NEW _____ Character value
Application . . . . . *LIST _____ Character value, *LIST
Release . . . . . _____ Number
Version . . . . . _____ Number
Create worklist . . . . . *NO _____ *NO, *YES
Form number . . . . . *NONE _____ Number, *NONE

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F10=Additional parameters   F12=Cancel
F13=How to use this display   F24=More keys
```

When you specify ***ACTIVE** value for the *List* parameter, the item is added to the active worklist, unless there isn't one, in which case it's added to the worklist that was last active.

TURNOVER® for iSeries v100 Commands

ADDTIMSHT Add Timesheet Entry

Add a timesheet entry to a resource's online timesheet.

```

                                Add Time Sheet Entry (ADDTIMSHT)

Type choices, press Enter.

Resource      *CURRENT_____ Name, *CURRENT
Date (000000 = Today)  000000      000000-999999
Project reference      _____ Project reference

                                Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

AUDITADJ Application Audit Adjustments and Report

This report is run to adjust TURNOVER® for iSeries v100's audit control file. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                TurnOver Audit Adjustments (AUDITADJ)

Type choices, press Enter.

Application . . . . . _____ Character value, *ALL
Release . . . . . 0 _____ Number
Version . . . . . 0 _____ Number
Level . . . . . *PROD _____ Number, *PROD, *ALL
Object . . . . . *ALL _____ Name, Generic*
Object Type . . . . . *ALL _____ Character value
Starting Date. . . . . 000000 _____ Date, 000000
Comment . . . . . _____

                                Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

AUDITRPT

Application Audit Report

This report prints any object or source member changed outside of TURNOVER® for iSeries v100's scope of control for the specified application. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Application Audit Report (AUDITRPT)

Type choices, press Enter.

Application . . . . . *ALL          Character value, *ALL
Release . . . . . 0              Number
Version . . . . . 0              Number
Level . . . . . *PROD           Number, *PROD, *ALL
Object . . . . . *ALL           Name, generic*, *ALL
Object Type . . . . . *ALL       Character value
Starting Date . . . . . 000000   Date, 000000
Outfile . . . . .              Name
Library name . . . . .          Name
Replace or add records . . . . . *ADD      *ADD, *REPLACE

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

BLDHLPCAT

Build Help Tree Category

Use this command to build a help tree category if you've changed it. This command is the same as selecting a help tree, category, or subcategory with option **14=Build**. (The contents of the tree and path fields vary depending on which one you select.) For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
Build Help Tree Category (BLDHLPCAT)

Type choices, press Enter.

Tree . . . . . Name, *ALL
Path . . . . . > *ALL

Replace Manual Matches . . . . . *NO      *YES, *NO
Remove excluded matches . . . . . *NO      *YES, *NO
Reset Match . . . . . *NO                *YES, *NO

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CHECKOUT Check Out Source

Use this command for both batch and interactive checkout processing from the Programmer Worklist (using option **21**). You can also use this command from the TURNOVER® for iSeries v100 command line to check out source by object or by source member.

```

                                Add TurnOver Checkout (CHECKOUT)

Type choices, press Enter.

Object . . . . . _____ Name
Type code . . . . . _____ AAUDIT, ABPGM, ADMDL, ADPGM...
Application . . . . . _____ CHAR
Level . . . . . _____ Number
Reference . . . . . _____ Char

                                Additional Parameters

Library . . . . . _____ *APPL      *APPL, name
Source Member . . . . . _____ *OBJ      Name, *OBJ, *OBJD
Source File . . . . . _____ *APPL      Name, *APPL
Source Library . . . . . _____ *APPL      Name, *APPL
Source copy option . . . . . _____ *NONE      *NONE, *ADD, *REPLACE
Duplicate non-src object . . . . . _____ *YES      *YES, *NO
Release . . . . . _____ Number
Version . . . . . _____ Number

                                                                More...

F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

CHGCATSTR Change Category Search String

Use this command to change an existing search string in a category's task selection criteria. This is the same as using option **2=Change** on the *Work with Category Search Strings* panel. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```

                                Change Category Search String (CHGCATSTR)

Type choices, press Enter.

Tree . . . . . _____ Name
Path . . . . . _____

Sequence . . . . . _____ Number
New String . . . . . _____ *SAME
New Sequence . . . . . _____ *SAME      Number, *SAME
Scope of search . . . . . _____ *SAME      *BOTH, *DESC, *DTLS, *SAME
Case sensitive search . . . . . _____ *SAME      *YES, *NO, *SAME

                                                                Bottom

F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CHGHLPCAT Change Help Tree Category

Use this command to change the task selection criteria for an existing help tree category. This command is the same as selecting either a help tree category or subcategory with option **2=Change**. (The tree and path fields vary depending on which one you select.) For more information about help trees, see the *Wisedesk* topic in **Chapter 9: Working with Projects and Tasks** of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
Change Help Tree Category (CHGHLPCAT)

Type choices, press Enter.

Tree . . . . . > DOCUMENT      Name
Path . . . . . > '/USERGUIDE/'

-----
Description . . . . . *SAME

Additional Parameters

Project . . . . . *SAME      Character value, *ALL...
+ for more values
Resource . . . . . *SAME      Character value, *ALL, *SAME
+ for more values
Requester . . . . . *SAME      Character value, *ALL, *SAME
+ for more values

More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

CHGHLPTREE Change Help Tree

Use this command to change the description of a help tree. This command is the same as selecting a help tree with option **2=Change**. For more information about help trees, see the *Wisedesk* topic in **Chapter 9: Working with Projects and Tasks** of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
Change Help Tree (CHGHLPTREE)

Type choices, press Enter.

Help tree . . . . . _____ Name
Description . . . . . *SAME

-----

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```


TURNOVER® for iSeries v100 Commands

CHGPWL Change Programmer Worklist

Use this command to change a programmer's worklist. For more information, see the topic *Programmer WorkList Manager* in the *TURNOVER® for iSeries v100 Developer's Guide*.

```
Change Programmer Worklist (CHGPWL)

Type choices, press Enter.

List _____ NAME
Description *SAME _____

Application *SAME Character value, *SAME
Release *SAME Number, *SAME
Version *SAME Number, *SAME
Programmer *SAME Name, *SAME

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

CHGPWLITM Change Programmer Worklist Item

Use this command to change an item (object or source entry) on the Programmer's Worklist. For more information, see the *Programmer WorkList Manager* topic in the *TURNOVER® for iSeries v100 Developer's Guide*.

```
Change Pgmr Worklist Item (CHGPWLITM)

Type choices, press Enter.

List . . . . . _____ Name
Object . . . . . _____ Character value
Attribute . . . . . _____ AAUDIT, ABPGM, ADMDL, ADPGM..
Application . . . . . *LIST Character value, *LIST
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number
New programmer . . . . . *SAME Name, *SAME
New reference . . . . . *SAME *SAME, Char
New description . . . . . *SAME _____

New user defined status . . . . *SAME *SAME, Char
X-Ref checked . . . . . *SAME *SAME, Y, N
Related applications checked . . *SAME *SAME, Y, N
Sequence . . . . . 1 1, 2
*Change all levels . . . . . *NO *YES, *NO Bottom

F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
* visible when you press F10
```

TURNOVER® for iSeries v100 Commands

CHGPWLPGMR Change Worklist Programmer

Use this command to reassign the programmer associated with a given worklist. Depending on the parameters you specify, TURNOVER® for iSeries v100 might make changes to the Worklist programmer and the Worklist item programmer for all lines on the worklist and checkout records. For more information about this command, see the online Help.

```
Change Worklist Programmer (CHGPWLPGMR)

Type choices, press Enter.

List . . . . . _____ Character value
To programmer . . . . . _____ Name
From programmer . . . . . *ALL Name, *ALL, *ITEM
Copy test source . . . . . *YES *YES, *NO

F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

CHGTOLIBL Change TURNOVER® for iSeries Liblist

Use this command to edit and change library list object names.

```
Change TURNOVER® Library List (CHGTOLIBL)

Type choices, press Enter.

Library list object . . . . . > *APPL Lib list name, *FORM, *APPL
Application . . . . . > AP Character value
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number

F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CHKAPPDFN Check Application Definition

This command can be run to verify objects in an application's library(s). For more information, see *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Check Application Definition (CHKAPPDFN)

Type choices, press Enter.

Application . . . . .
Release . . . . . *LAST      Character value
Version . . . . . *LAST      *LAST, Release Number
Level . . . . . *PROD       Number, *LAST
Detail . . . . . *ALL        Number, *PROD
                                *ALL, *OBJNAMSTD, *JOB1...
                                + for more values

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

CHKCHGOBJ Check Changed Object

This command checks for objects that are currently checked out to one programmer (usually the person who runs it) which were changed by another programmer during the time the first programmer had the objects checked out. For more information, see the *Multiple Programmer Checkout Facility* topic in the *TURNOVER® for iSeries v100 Supplement* entitled *Emergency Changes in TURNOVER® for iSeries v100 (#24)*.

```

                                Check Changed Objects (CHKCHGOBJ)

Type choices, press Enter.

Programmer . . . . . *USRPRF   Name, *USRPRF

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

| | |
|-----------------|---------------------------|
| CHKINMBR | Check-in by Member |
|-----------------|---------------------------|

No command parameters. This command provides an alternate path to the *Check in Source Members* panel. See *Chapter 5: Checking Out/Checking In Source* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|-----------------|---------------------------|
| CHKINOBJ | Check-in by Object |
|-----------------|---------------------------|

No command parameters. This command provides an alternate path to the *Check in Source for Production Object* panel. See *Chapter 5: Checking Out/Checking In Source* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|------------------|----------------------|
| CHKOUTDFU | Check Out DFU |
|------------------|----------------------|

This command is used exclusively for checking out S/36 DFU types. See *Chapter 5: Checking Out/Checking In Source* in the *TURNOVER® for iSeries v100 User Guide*.

```
Checkout DFU (CHKOUTDFU)

Type choices, press Enter.

DFU . . . . . _____ Name
Application code . . . . . _____ Name
Release . . . . . _____ Number
Version . . . . . _____ Number
Reference . . . . . _____ Char, *SELECT

                                     Bottom
F3=Exit  F4=Prompt  F5=Refresh  F10=Additional parameters  F12=Cancel
F13=How to use this display  F24=More keys
```

TURNOVER® for iSeries v100 Commands

CHKOUTMEN Check Out S/36 Menu

This command is used exclusively for checking out S/36 menu types. See *Chapter 5: Checking Out/Checking In Source* in the *TURNOVER® for iSeries v100 User Guide*.

```
Checkout S/36 Menu (CHKOUTMEN)

Type choices, press Enter.

MENU . . . . . _____ Name
Library . . . . . *APPL _____ Name, *APPL, *LIBL
Programmer . . . . . *USRPRF _____ Name, *USRPRF, *SELECT
Source checkout library . . . . . *APPL _____ Name, *PGMR, *APPL
Application code . . . . . _____ Name
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number
Reference . . . . . _____ Char, *SELECT

Additional Parameters

Bypass Prompt . . . . . _ Y,N

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

CHKOUTMSG Check Out Message ID

This command checks out one or more message IDs from a message file. This command, which you can enter on a command line, is used for checking out messages within PWM. See the *TURNOVER® for iSeries v100 Supplement* entitled *Handling Message IDs in TURNOVER® for iSeries v100 (#61)*.

```
Checkout Message ID (CHKOUTMSG)

Type choices, press Enter.

Message ID . . . . . *SELECT Message ID, *SELECT
Type code . . . . . _____ MSGID
Application . . . . . _____ Character value
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number
Reference . . . . . _____ Character value, *SELECT

Additional Parameters

Programmer . . . . . *USRPRF User profile, *USRPRF
Copy option . . . . . *ADD *NONE, *ADD, *REPLACE

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CMPSRCMBR Compare Source Members

This command compares two source members, producing a delta of the two members. Use this command to produce a report or an outfile containing the delta.

```
Compare Source Members (CMPSRCMBR)

Type choices, press Enter.

Reference file . . . . . _____ Name
Library . . . . . _____ Name, *LIBL
Reference member . . . . . _____ Name
Compare file . . . . . _____ Name
Library . . . . . _____ Name, *LIBL
Compare member . . . . . _____ Name, *REFMBR
Lines of context . . . . . 0 Number
Include comments . . . . . *YES *YES, *NO
Display output . . . . . *NO *YES, *NO
Print output . . . . . *YES *YES, *NO
Produce outfile . . . . . *NO *YES, *NO
Print cover page . . . . . *YES *YES, *NO
Print statistics . . . . . *YES *YES, *NO

F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

CPYHLPTREE Copy Wisedesk Tree

Use this command to copy a help tree and all of its categories to create a new tree. You must have **Add** project authority to perform this operation. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
Copy Wisedesk Tree (CPYHLPTREE)

Type choices, press Enter.

From tree . . . . . _____ Name
To Tree . . . . . _____ Name
New description . . . . . _____

F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CPYPWL Copy Programmers Worklist

Use this command to copy an existing Programmer Worklist to a new worklist. See the *Programmer Worklist Manager* topic in the *TURNOVER® for iSeries v100 Developer's Guide*.

```
Copy Programmer Worklist (CPYPWL)

Type choices, press Enter.

List . . . . . _____ Name
Copy to list . . . . . _____ Name

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

CPYPWLITM Copy Programmer Worklist Item

Use this command to copy an item from one worklist to another. See the *Programmer Worklist Manager* topic in the *TURNOVER® for iSeries v100 Developer's Guide*.

```
Copy Pgmr Worklist Item (CPYPWLITM)

Type choices, press Enter.

List . . . . . _____ Name
Copy to list . . . . . _____ Name
Object . . . . . _____ Character value
Attribute . . . . . _____ AAUDIT, ABPGM, ADMDL, ADPGM...
Application . . . . . *LIST Character value, *LIST
Release . . . . . _____ Number
Version . . . . . _____ Number

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CPYTOLLO Copy TURNOVER® Library List

Use this command to copy a library list object to create a new library list object.

```
Copy Library List Object (CPYTOLLO)

Type choices, press Enter.

From library list object . . . .   _____   Library list name
To library list object . . . .   _____   Library list name

F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

CPYTSTDTA Copy Test Data to Production File

Use this command only as a post-run command on a TURNOVER® for iSeries v100 form to copy data from a test file to a production file. This command does *not* distribute data. (To do that, set the parameter on the TURNOVER® for iSeries v100 form line, *Copy file FMTOPT*, to ***FROMFILE**.)

```
Copy Test Data (CPYTSTDTA)

Type choices, press Enter.

File . . . . . _____   Name

F9=All parameters   F11=Keywords   F14=Command string   F24=More keys
```


TURNOVER® for iSeries v100 Commands

CRTAPPDFN Create Application Definition

This command creates application definitions based on models provided with your system. See the *TURNOVER® for iSeries v100 Application Planning Guide*.

```

                                Create Application Definition (CRTAPPDFN)

Type choices, press Enter.

New Application . . . . . _____ CHAR
  Release . . . . . 0 _____ Number
  Version . . . . . 0 _____ Number
Model on . . . . . *SELECT CHAR, *SELECT
  Release . . . . . 0 _____ Number
  Version . . . . . 0 _____ Number
New application description . . *MODEL
-----
Edit Authority . . . . . *YES *YES, *NO
Edit Distribution List . . . . *YES *YES, *NO
Edit Approval List . . . . . *YES *YES, *NO
Submit Initial Build . . . . . *YES *YES, *NO
Create remote appl. definition *YES *YES, *NO
Show missing items . . . . . *YES *YES, *NO

                                Bottom

F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

CRTDEMOENV Create Demo Environment

This command is to create demonstration/training environments for a TURNOVER® for iSeries v100 Training Workshop. This command requires additional libraries from UNICOM Systems, Inc. and can be used only by permission.

```

                                CREATE DEMO ENVIRONMENT (CRTDEMOENV)

Type choices, press Enter.

Demo Prefix . . . . . _____ Demo Prefix i.e. "T1","ZP"

                                Bottom

F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CRTFTFIL

Create FASTTASK Files on Production Computer

Use this command to set up DDM files so you can enter problems and requests into your production computer's project system that point back to project files on your development computer.

```
                Create Fasttask DDM Files (CRTFTFIL)

Type choices, press Enter.

Remote location name . . . . . _____ Name
DDM file library . . . . . _____ Name
Hold file library . . . . . _____ Name

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

CRTPWL

Create a Programmer Worklist

Use this command to create a Programmer Worklist. You can also do so by selecting option **20** on the *Work with Project* panel and **F6** on *Work with Programmer Worklists*.

```
                Create Programmer Worklist (CRTPWL)

Type choices, press Enter.

List . . . . . *SELECT      Name, *SELECT
Description . . . . . *PROJECT

Application . . . . . *PROJECT  Character value, *PROJECT
Release . . . . . _____  Number
Version . . . . . _____  Number
Programmer . . . . . *PROJECT  Name, *PROJECT, *USRPRF

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

CRTRCVFORMI Create Recovery Form (Interactively)

This command lets you interactively build a recovery form to undo changes that were installed by a previously run form. When you run the recovery form, it reverses the changes made by the first run.

```

                                Create Recovery Form (CRTRCVFORMI)

Type choices, press Enter.

Form to recover . . . . . _____ Form number
Run recovery form . . . . . *NO      *YES, *NO, *INTER
Error-check form . . . . . *YES     *YES, *NO
Distribute form . . . . . *APPL    *APPL, *YES, *NO
Checkout . . . . . *NO           *NO, *BATCH, *INTER

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

CUSTFKEY Set Custom Fkey (F15) on PWM Panel

This command customizes the **F15** key on the *Programmer Worklist Manager* panel. For example, you may want to use it to obtain quick access to the Pathfinder or Abstract/Probe system.

```

                                Customize FKey Definition (CUSTFKEY)

Type choices, press Enter.

User . . . . . *ALL      Name, *ALL
Program . . . . . *ALL   Name, *ALL
Text . . . . . *SAME
Command to execute . . . . . *SAME

-----
Function . . . . . *SET      *SET, *CANCEL

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

DISTDATA

Distribute Data

Use this command as a post-run command on a TURNOVER® for iSeries v100 form to distribute data with a physical file (PF) to a remote system. TURNOVER® for iSeries v100 will distribute data for the physical file you specify for the *File* parameter. For more information about this command, see the online Help.

```

                                Distribute Data (DISTDATA)

Type choices, press Enter.

File . . . . . _____ Name

                                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

DLTCATSTR

Delete Category Search String

Use this command to delete an existing search string in a category's task selection criteria. This is the same as using option **4=Delete** on the *Work with Category Search Strings* panel. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```

                                Delete Category Search String (DLTCATSTR)

Type choices, press Enter.

Tree . . . . . _____ Character value
Path . . . . . _____
_____
_____
Sequence . . . . . _____ Number, *ALL

                                Additional Parameters

Search String . . . . . _____

                                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

DLTHLPCAT Delete Help Tree Category

Use this command to delete an existing help tree category. This command is the same as selecting either a help tree category or subcategory with option **4=Delete**. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
                Delete Help Tree Category (DLTHLPCAT)

Type choices, press Enter.

Tree . . . . . _____ Character value
Path . . . . . _____
_____
_____

                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

DLTHLPTREE Delete Help Tree

Use this command to delete an existing help tree. This command is the same as selecting a help tree with option **4=Delete** on the *Work with Help Trees* panel. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
                Delete Help Tree (DLTHLPTREE)

Type choices, press Enter.

Help tree . . . . . _____ Character value

                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

DLTPWL Delete Programmer's Worklist

Use this command to delete a programmer's worklist. See the *Programmer Worklist Manager* topic in the *TURNOVER® for iSeries v100 Developer's Guide*.

```

                                Delete Programmer Worklist (DLTPWL)

Type choices, press Enter.

List . . . . . _____ Name

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

DSPCHKOUT Display Checked Out Members

No command parameters. This command displays the *View Checked Out Members* panel. See *Chapter 5: Checking Out/Checking In Source* in the *TURNOVER® for iSeries v100 User Guide*.

DSPCOHST Display Checkout History

This command displays all checkout and check-in history for any object or source member.

```

                                Display Checkout History (DSPCOHST)

Type choices, press Enter.

Source File . . . . . _____ Name
Library . . . . . _____ Name
Member . . . . . _____ Name

                                Additional Parameters

Object . . . . . _____ Name
Library . . . . . _____ Name
Type . . . . . _____ Name

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

DSPFRMROL Display Rollover Notification

This command displays the form number threshold and message frequency information that's contained in the CHKFRMNUM data area. For more information, see the online Help for both this command and the **SETFRMROL** command.

```
11/03/98                                            Display Rollover Notification                                            Your Company, Inc.  
16:14:37                                                                                                                                  SYSTEM: SLS  
  
Notify at form number   . . . . . 9900  
Notify every multiple of   . . . . . 010  
Change notification at form #   . . . . . 9950  
Notify every multiple of   . . . . . 005  
  
F3=Exit    F12=Cancel
```

DSPRELTO Display Current Release Information

No command parameters. This command displays the current release of TURNOVER® for iSeries v100 on your system. Alternate path is Main Menu option **8**, then option **6**.

DSTFOR Distribute Forms

No command parameters. Alternate path is Distribution Menu option **2**.

TURNOVER® for iSeries v100 Commands

DUPREFOBJ Create Duplicate Reference Objects in Production Library

Use this command to copy reference objects from library **SOFTTURN** to a library you specify. **TURNOVER®** for iSeries v100 changes the object owner to a user profile name you specify. You're prompted to edit the object authority for each of the objects duplicated. For more information, see the *TURNOVER® for iSeries v100 Application Planning Guide*.

```
                Create Duplicate Ref Object (DUPREFOBJ)

Type choices, press Enter.

To Library . . . . . _____ Library
Object Owner . . . . . _____ User Profile

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

DUPTSTOBJ Duplicate Test Objects

Use this command to duplicate test objects delivered with **TURNOVER®** for iSeries v100 from the library SAVETEST to DEVTEST, ACPTTEST, and PRODTEST demonstration test libraries.

No parameters. User must be signed on as QSECOFR or have *SECOFR authority.

FASTTASK FASTTASK Project Entry Command

No Parameters. Access to the **FASTTASK** Helpdesk problem/request entry function. See *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

HELPDESK Enter TURNOVER® Helpdesk Function

There are no parameters for this command. This command is a menu command that displays the Helpdesk requester database.

LISTAUTH List Authorized TURNOVER® Users

There are no parameters for this command. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

LISTDFTS List Application Definitions

This command submits a report to print Application Definitions. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                List Default Values (LISTDFTS)

Type choices, press Enter.

Application code . . . . . *ALL      Application code, *ALL
Release . . . . . _____      Number
Version . . . . . _____      Number
Level . . . . . *ALL             Number, *PROD, *ALL
Defaults to list . . . . . *ALL_____ *ALL, *DESC, *SYSTEM...

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

LISTFORMS List TURNOVER® Forms

This command is use to submit a report to list one or more TURNOVER® for iSeries v100 forms. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                List TurnOver Forms (LISTFORMS)

Type choices, press Enter.

Application . . . . . *ALL      Appl, *ALL
Release . . . . . 0           Rel
Version . . . . . 0           Ver
Level . . . . . *ALL         Lev, *PROD, *ALL
Reference . . . . . *ALL      Char, *ALL, generic*
From form . . . . . 1         number
To form . . . . . 9999999    number
From date . . . . . 000000   Date, 000000
To date . . . . . 999999    Date, 999999
Programmer . . . . . *ALL     Ustrprf, *ALL
+ for more values
Job accounting code . . . . . *ALL
+ for more values
Form status . . . . . *ALL     *ALL, APLPN, CANCEL, ...
+ for more values
Form Detail Level . . . . . *LINE *FORM, *LINE, *FULL

                                More...
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

LISTPGMRS List TURNOVER® Programmers

No Parameters for this command. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

MOVPWLITM Move Programmer Worklist Item

This command moves a Programmer's Worklist item from one worklist to another. For more information, see the topic *Programmer Worklist Manager* topic in the *TURNOVER® for iSeries v100 Developer's Guide*.

```

                                Move Pgmr Worklist Item (MOVPWLITM)

Type choices, press Enter.

List . . . . . _____ Name
Move to list . . . . . _____ Name
Object . . . . . _____ Character value
Attribute . . . . . _____ AAUDIT, ABCDTA, ABPGM, ADMD...
Application . . . . . *LIST Character value, *LIST
Release . . . . . _____ Number
Version . . . . . _____ Number

                                Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

MRGSRM CMBR Merge Source Member

This command merges three or more source members into one new member.

```

                                Merge Source Members (MRGSRM CMBR)

Type choices, press Enter.

Reference file . . . . . _____ Name
  Library . . . . . _____ Name, *LIBL
Reference member . . . . . _____ Name
Primary compare file . . . . . _____ Name, *REFFILE
  Library . . . . . _____ Name, *LIBL, *REFLIB
Primary compare member . . . . . _____ Name, *REFMBR
Secondary compare file . . . . . _____ Name, *REFFILE
  Library . . . . . _____ Name, *LIBL, *REFLIB
Secondary compare member . . . . . _____ Name, *REFMBR
Merge file . . . . . _____ Name, *REFFILE
  Library . . . . . _____ Name, *LIBL, *REFLIB
Merge member . . . . . _____ Name, *REFMBR
Merge file option . . . . . *REPLACE *REPLACE, *ADD
Include merge comments . . . . . *YES *YES, *NO

                                Bottom
F3=Exit  F4=Prompt  F5=Refresh  F10=Additional parameters  F12=Cancel
F13=How to use this display  F24=More keys
```

TURNOVER® for iSeries v100 Commands

PRGFOR Purge TURNOVER® Forms

This command purges history records from TURNOVER® for iSeries v100's files. **Use caution** to avoid purging important change history. Alternate path: Main Menu option **8**, then option **1**.

```

                                Purge TurnOver Forms (PRGFOR)

Type choices, press Enter.

Application . . . . . _____ Name, *ALL
Release . . . . . 00          00-99
Version . . . . . 00          00-99
Level . . . . . 00          00-99
+ for more values _____
                                00
                                00
                                00

Purge Date . . . . . _____ Date
From Form-# . . . . . 1          Number
To Form-# . . . . . 9999999      Number
Form Status . . . . . C          C=Cncl, R=Run, P=Pend, A=C/R/P
Retain Object History . . . . . Y      Y,N

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

PRJCSTRPT Project Cost Report

This command submits a job to report project task costs, projected or actual. See **Chapter 10: TURNOVER® for iSeries v100 Reports** in the **TURNOVER® for iSeries v100 User Guide**.

```

                                TurnOver Project Cost Report (PRJCSTRPT)

Type choices, press Enter.

Project . . . . . *ALL          Char, *ALL
Task . . . . . *ALL          Char, *ALL
SubTask . . . . . *ALL         Char, *ALL
Status . . . . . *ALL         Code, *ALL
+ for more values _____

Resource . . . . . *ALL          Resource ID, *ALL
+ for more values _____

Requestor . . . . . *ALL          Requestor ID, *ALL
+ for more values _____

From date . . . . . 000000       Date, 000000
To date . . . . . 999999       Date, 999999
Calculation method . . . . . *TIMESHEET *TIMESHEET, *PROJECT
Print Selection Criteria . . . . . Y      Y, N

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

PRJPTYRPT Project Priority Report

This command submits a report of project tasks, in priority order by resource. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Priority Report (PRJPTYRPT)

Type choices, press Enter.

Resource (User-Id) . . . . . *ALL          Name, *ALL
      + for more values
From Project/Task/Subtask . . . *START      ProjTaskSb, *START
To   Project/Task/Subtask . . . *PRJEND    ProjTaskSb, *PRJEND, *END
From Priority . . . . . 1          Priority Range
To   Priority . . . . . 9          Priority Range
Status Codes . . . . . -          Status, Blank for All
      + for more values
Summary Description? . . . . . Y          Y, N
Page Break on Task and Subtask . N          Y, N
Print Selection Criteria . . . . . Y          Y, N

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

PRJRSRTIM Project Resource Time Report

This command submits a report of time reported for one or more project resources. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Project Resource Time Report (PRJRSRTIM)

Type choices, press Enter.

Resource (User-Id) . . . . . *ALL          Ushrpf, *ALL
      + for more values
Project . . . . . *ALL          Char, *ALL
Task . . . . . *ALL          Char, *ALL
SubTask . . . . . *ALL          Char, *ALL
Status . . . . . *ALL          Code, *ALL
      + for more values
From date . . . . . 000000         Date, 000000
To date . . . . . 999999         Date, 999999
Print Selection Criteria . . . . . Y          Y, N
Only print summary info . . . . . N          Y, N
Page break on resource . . . . . N          Y, N

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

| | |
|------------------|----------------------------|
| PRJTSKRPT | Project Task Report |
|------------------|----------------------------|

See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*. Alternate path: option **10** on the Main Menu, then option **10** on the Reporting Menu.

| | |
|------------------|---------------------------------|
| PRTHLPCAT | Print Help Tree Category |
|------------------|---------------------------------|

Use this command to print a report showing the category's selection criteria or task list. This command is the same as selecting either a help tree category or subcategory with option **6=Print**. For more information about help trees, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*. For more information about this command, see the online Help.

```
Print Help Tree Category (PRTHLPCAT)

Type choices, press Enter.

Tree . . . . . _____ Name
Path . . . . . _____

-----
Print selection criteria . . . . *YES      *YES, *NO
Print matching tasks . . . . . *YES      *YES, *NO

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

PRTHLPTRREE **Print Help Tree**

Use this command to print a listing showing all the categories and subcategories defined for a specific help tree, as well as the task lists associated with them. This is the same as selecting a help tree with option **6** on the *Work with Help Trees* panel.

```
Print Helptree Structure (PRTHLPTRREE)

Type choices, press Enter.

Tree . . . . . _____ Character value

                                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

RCVFOR **Receive Forms**

No parameters. Alternate path: Distribution Menu option **3**.

REFACTRPT **Reference Activity Report**

This command produces a report of all source checkout and object promotion activity related to a particular reference Project or tasks.

RESETFOR **Reset TURNOVER® Form**

The command parameter is the form number. This command resets the form status from **RECOVER** to **RECVD** for a form that was distributed from another computer but didn't run successfully. (This might happen if a file is in use when the form started to run, for example.)

RGZTOFILES **Reorganize TURNOVER® Files**

No parameters. This command submits a reorganize file job to batch. Be sure that no one is working with TURNOVER® for iSeries v100 and that no TURNOVER® for iSeries v100 forms or TURNOVER® for iSeries v100 distributions are running when you run this reorganize job. There are no parameters for this command.

TURNOVER® for iSeries v100 Commands

RNMAPP

Rename an Application

This command lets you rename an application. It updates all of the associated files and history to the new application code you provide. See the online help for this command for more information.

```

                                Rename Application (RNMAPP)

Type choices, press Enter.

From application . . . . . _____ Character value
From release . . . . . 0 _____ Number
From version . . . . . 0 _____ Number
From level . . . . . 0 _____ Number, *ALL
To application . . . . . *SAME _____ Character value, *SAME
To release . . . . . *SAME _____ Number, *SAME
To version . . . . . *SAME _____ Number, *SAME
To level . . . . . *SAME _____ Number, *SAME

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

RPTFORMDST

Report Form Distribution

This command submits a report of distribution form history for one or more applications. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Report Form Distribution (RPTFORMDST)

Type choices, press Enter.

Application . . . . . *ALL _____ Appl, *ALL
Release . . . . . 0 _____ Rel
Version . . . . . 0 _____ Ver
Level . . . . . 0 _____ Lev
Target System . . . . . *ALL _____ System name, *ALL
Reference . . . . . *ALL _____ Char, *ALL, generic*
From form . . . . . 1 _____ number
To form . . . . . 9999999 _____ number
Programmer . . . . . *ALL _____ Usrprf, *ALL
Form status . . . . . *ALL _____ *ALL, APLPN, CANCEL, ...
+ for more values
Detail Level . . . . . *BASIC _____ *BASIC, *FULL
From date . . . . . 000000 _____ Run date
To date . . . . . 999999 _____ Run date
Print Selection Criteria . . . . . Y _____ Y, N

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

RPTOBJDST Report Object Distribution

This command submits a job to report object distribution history, by application, by object or for a particular Project reference. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Report Object Distribution (RPTOBJDST)

Type choices, press Enter.

Application . . . . . *ALL      Appl, *ALL
Release . . . . . 0          Rel
Version . . . . . 0          Ver
Level . . . . . 0           Lev
Target System . . . . . *ALL   System name, *ALL
Reference . . . . . *ALL     Char, *ALL, generic*
Object . . . . .           Name, *ALL
  Library . . . . . *ALL     Name, *ALL
      + for more values

Object type . . . . . *ALL   *ALL, *FILE, *PGM ...
From date . . . . . 000000   Date, 000000
To date . . . . . 999999    Date, 999999
Print Selection Criteria . . . . . Y      Y, N

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

RPTOBJHST Report Object History

This command submits a job to report object change history, by application, by object or for a particular Project reference. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Report Object TurnOver History (RPTOBJHST)

Type choices, press Enter.

Application . . . . . *ALL      Appl, *ALL
Release . . . . . 0          Rel
Version . . . . . 0          Ver
Level . . . . . *ALL       Number, *PROD, *ALL
Reference . . . . . *ALL     Char, *ALL, generic*
Object . . . . .           Name, *ALL
  Library . . . . . *ALL     Name, *ALL
      + for more values

Object type . . . . . *ALL   *ALL, *FILE, *PGM ...
From date . . . . . 000000   Date, 000000
To date . . . . . 999999    Date, 999999
Detail . . . . . *BASIC     *BASIC, *FULL
Print Selection Criteria . . . . . Y      Y, N

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```


TURNOVER® for iSeries v100 Commands

RPTPGMRHST Report Programmer History

This command submits a job to report object change history, by programmer, by object or for a particular Project reference. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Report Programmer History (RPTPGMRHST)

Type choices, press Enter.

Programmer . . . . . *ALL      Ushrprf, *ALL
+ for more values   _____
Reference . . . . . *ALL      Char, *ALL, generic*
Object . . . . . *ALL      Name, *ALL
Library . . . . . *ALL      Name, *ALL
+ for more values   _____
Object type . . . . . *ALL      *ALL, *FILE, *PGM ...
From date . . . . . 000000    Date, 000000
To date . . . . . 999999    Date, 999999
Detail . . . . . *BASIC     *BASIC, *FULL
Print Selection Criteria . . . . . Y      Y, N

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

RPTSRCUSE Report Source Checkout History

This command submits a job to report source checkout history, by application, by object or for a particular Project reference. See *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Report Source Checkout History (RPTSRCUSE)

Type choices, press Enter.

Application . . . . . *ALL      Application, *ALL
Release . . . . . 0          Release
Version . . . . . 0          Version
Level . . . . . *ALL      Number, *PROD, *ALL
Source Member . . . . . *ALL    Name, Generic*, *ALL
+ for more values   _____
Source File . . . . . *ALL      Name, *ALL
Library . . . . . *ALL      Name, *ALL
+ for more values   _____
Object type . . . . . *ALL      *ALL, *FILE, *PGM ...
Programmer . . . . . *ALL      Ushrprf, *ALL
+ for more values   _____
From date . . . . . 000000    Date, 000000
To date . . . . . 999999    Date, 999999
Status . . . . . *ALL      *IN, *OUT, *ALL

More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

RSTARCSRC Restore Archived Source

This command restores a member from the off-line source archive. You can get the parameter information you need (*Archive alias, Tape volume*) from option 8 on the *Work with Object History* panel. For more information, see *Chapter 4: Work with Object History* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                RESTORE ARCHIVED SOURCE (RSTARCSRC)

Type choices, press Enter.

Source archive file . . . . . *DEFAULT      Name, *DEFAULT
  Library name . . . . . *LIBL             Name, *LIBL
Member . . . . . _____
Archive alias . . . . . _____
Tape volume . . . . . _____
Device . . . . . _____ Name
Restore File . . . . . _____ Name
  Library . . . . . _____ Name

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

SAVARCO

Save Archive Objects

This command saves archived objects off line; it is the same command used for option **9** on the Utility Menu.

If you elect to archive objects, TURNOVER® for iSeries v100 does not delete the temporary library it creates during the form run. That library becomes the object archive library, which is named TnnnnnnnD (where nnnnnnn is the TURNOVER® for iSeries v100 form number). When you run this command, TURNOVER® for iSeries v100 saves libraries you have selected to media and maintains a list of archived objects by form number.

Note: After TURNOVER® for iSeries v100 saves the archive libraries you have selected, it redisplay the list of libraries. You can then select saved libraries that you want to delete. Alternatively, you can use the **SAVARSBM** command to save and delete the object archive libraries (see page 44).

If you specify *DELETE for the *Device* parameter, TURNOVER® for iSeries v100 will delete the archive libraries *without* saving them first.

An end-of-tape parameter lets you control what happens to the tape at the end of the save operation.

TURNOVER® for iSeries v100 can use the objects in the TURNOVER® for iSeries v100 library to reverse (undo) the changes made on a TURNOVER® for iSeries v100 form. See also **Work with Forms** option **12=Create recovery form**. Alternate path: Utility Menu option **9**.

```
Submit Object Archive Save (SAVARSBM)

Type choices, press Enter.

Form . . . . . *ALL          number
From date . . . . . 000000    Date, 000000
To date . . . . . 999999    Date, 999999
Volume . . . . .           Character value, *MOUNTED
Device . . . . .           Character value, *DELETE
Delete archive after save? . . . 'Y'      Y or N
End of tape option . . . . . REWIND    REWIND, UNLOAD, LEAVE

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

Retrieve objects you've stored off line using option **10** on the Utility Menu.

TURNOVER® for iSeries v100 Commands

SAVARSBM Submit Object Archive Save

This command lets you save objects off line that have been archived after a form run (this includes both Tform#D libraries and archived explode libraries), and then delete the archives after the save. This command runs in batch.

```

                                Submit Object Archive Save (SAVARSBM)

Type choices, press Enter.

Form . . . . . *ALL          number
From date . . . . . 000000     Date, 000000
To date . . . . . 999999     Date, 999999
Volume . . . . .             Character value, *MOUNTED
Device . . . . .             Character value, *DELETE
Delete archive after save? . . . 'Y'          Y or N
End of tape option . . . . . REWIND     REWIND, UNLOAD, LEAVE

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

SETFRMROL Set Form Rollover Notification

This command lets you set the form number threshold, and the message frequency, for notifying TURNOVER® for iSeries v100 users that their system form numbering will shortly return to 1. These values are stored in the CHKFRMNUM data area. For more information about this command, see the online Help.

```

                                Set Form Rollover Notification (SETFRMROL)

Type choices, press Enter.

Notify at form number . . . . . 9900          1-9999
Notify every multiple of . . . . . 010        001-999
Change notification at form # . . . 9950      Number
Notify every multiple of . . . . . 005        Number

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

| | |
|-----------------|------------------------------|
| SETGLOBE | Set Global Parameters |
|-----------------|------------------------------|

This command controls some TURNOVER® for iSeries v100 system defaults. Alternate path: option **5** on the Utility Menu. For information about the parameters, see *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|---------------|--|
| STRPWM | Start Programmer Worklist Manager |
|---------------|--|

This command starts the *Programmer Worklist Manager* function. It displays the *Work with Programmer's Worklist* panel. For more information, see the *TURNOVER® for iSeries v100 Developer's Guide*.

```
                Start Programmer Worklist Mgr. (STRPWM)
Type choices, press Enter.
List . . . . . *PGMR _____ Name, *PGMR, *PRV
                Additional Parameters
Environment . . . . . *PRV _____ *PRV, ADVANTAGE, BAUMGARTEN...

                                                    Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

STRSYN

Start Synchronizer

This command starts the *Synchronizer* system function. It displays the Synchronizer Main Menu.

```
Start Synchronizer (STRSYN)

Type choices, press Enter.

Option . . . . . *NONE          *NONE, 1, 2, 3, 4, 5, 6, 7...

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TADDNEWS

Add News Item

Use this command to post news items to the EXPRESSDESK® for iSeries v100 Welcome page. You can use this command in an escalation table to have TURNOVER® for iSeries v100 automatically post a notice when an event (such as a change in status) occurs for a task.

```
Add News Item (TADDNEWS)

Type choices, press Enter.

Project . . . . . _____ Character value
Task . . . . . _____ Character value
Subtask . . . . . _____ Character value
Start Date . . . . . *NOW_____ Date, *NOW
Start Time . . . . . *NOW_____ Time, *NOW
End Units . . . . . *DAYS_____ *MINUTES, *HOURS, *DAYS...
End Value . . . . . 14_____ Number
Replace Existing Item . . . . . N_____ Y, N

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

For more information, see the section entitled *Maintaining News Items* in *Chapter 4: Customizing EXPRESSDESK® for iSeries v100* of the *EXPRESSDESK® for iSeries v100 Getting Started* guide. Also, see the online Help for this command.

TURNOVER® for iSeries v100 Commands

TADJPWLITM Adjust Worklist Item

Use this command to update existing worklists after an application definition's structure its library names.

```
Adjust Pgmr Worklist Item (TADJPWLITM)

Type choices, press Enter.

List . . . . . *ACTIVE      Name
Object . . . . . *ALL       Character value, *ALL
Attribute . . . . . *ALL     AAUDIT, ABPGM, ADMDL, ADMDL...
Application . . . . . *ALL    Character value, *ALL
Release . . . . . *ALL      Number, *ALL
Version . . . . . *ALL      Number, *ALL
Programmer . . . . . *SAME   Name, *SAME, *LIST

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

For more information, see the online Help.

TARAFORM Add Related Applications Forms

Use this command to create related application forms once the base form has been created. For more information about this command, see the online Help.

```
Add related applications forms (TARAFORM)

Type choices, press Enter.

Base form . . . . .          Number
Mode to run . . . . . *INTER *INTER, *BATCH

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TCFMFORM

Confirm Form

This command sends a confirmation message for a TURNOVER® for iSeries v100 form to the TURCRARE autostart job – either on the same computer, or on another computer. You might use this command on a command line or within an exit program.

```

                                Confirm Form (TCFMFORM)

Type choices, press Enter.

Form number . . . . . _____ Number
System name . . . . . _____ *LOCAL *LOCAL, System name
Form status . . . . . _____ *CURRENT *CURRENT, Form status
Environment . . . . . _____ *CURRENT *CURRENT, Environment
Date/time . . . . . _____ *CURRENT
Function . . . . . _____ *RUN *CREATE, *COPY, *APPROVE...
Copied to form number . . . . . _____ Number
Distributed to system name . . . . . _____ Character value
Distributed to system number . . . . . _____ Number
Send confirmation to system . . . . . _____ *SENDER *SENDER, System name
Send confirmation to User ID . . . . . _____ *TOMSGRCV *TOMSGRCV, User ID

                                Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```


TURNOVER® for iSeries v100 Commands

| |
|--|
| TCHGCMMTH Change CM Method |
|--|

Use this command to change the name of the program, the name of its library, or the names of both the program and library you want TURNOVER® for iSeries v100 to call when executing a change management method (such as moving an object, copying an object, deleting an object, and so forth) for an object. This applies specifically to an object with a TURNOVER® for iSeries v100 global type code definition that references the change management scheme you are working with. (You must have TURNOVER® for iSeries v100 **System Defaults** authority to change CM methods.) For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Change CM Method (TCHGCMMTH)

Type choices, press Enter.

Scheme . . . . . > UTMENU           Name
Method . . . . . > *CHGOBJ         *ARCHIVE, *BROWSE, *CHGOBJ, ...
Method Program . . . . . > *DEFAULT   Name, *SAME, *DEFAULT...
Library . . . . . > *DEFAULT       Name, *SAME, *DEFAULT...

                                           Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TCHGCMSCH Change CM Scheme

Use this command to change a change management scheme. (You must have TURNOVER® for iSeries v100 **System Defaults** authority to change CM schemes.) A change management scheme allows you to override change management methods (such as moving an object, copying an object, deleting an object, and so forth) for a user-defined object type. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types* (#59).

```
Change CM Scheme (TCHGCMSCH)

Type choices, press Enter.

Scheme . . . . . > UTMENU           Name
Description . . . . . > 'Menu System Scheme'
-----
Default Program . . . . . > *TURNOVER       Name, *SAME, *NONE, *TURNOVER
Library . . . . . > UTMENUPRD       Name, *SAME, *SCHEMELIB

                                           Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TCHKOUTIFS Check Out IFS Object

Use this command to check out IFS objects. For detailed information, see the IFS guide, *Managing Integrated File System (IFS) Objects Using TURNOVER® for iSeries v100*.

```
Check Out IFS Object (TCHKOUTIFS)

Type choices, press Enter.

Object . . . . . _____
-----
Type code . . . . . _____ CLASS, DLL, EXE, HLP, HTML,...
Application . . . . . _____ Character value
Reference . . . . . _____ Character value

                                           Bottom
F3=Exit  F4=Prompt  F5=Refresh  F10=Additional parameters  F12=Cancel
F13=How to use this display  F24=More keys
```

TURNOVER® for iSeries v100 Commands

TCPYCMSCH Copy Change Management Scheme

Use this command to create a new change management scheme by copying an existing scheme. (You must have TURNOVER® for iSeries v100 **System Defaults** authority to copy CM schemes.) For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Copy CM Scheme (TCPYCMSCH)

Type choices, press Enter.

From scheme . . . . . > UTMENU      Name
To scheme . . . . . _____      Name

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TCPYPRJ Copy Project

Use this command to copy a project entry to create a new project entry. Associated tasks are not copied and links are not created between tasks. Do *not* use this command to rename a project.

```
Copy Project (TCPYPRJ)

Type choices, press Enter.

From project . . . . . _____      Character value
To project . . . . . _____      Character value
Copy tasks and subtasks . . . . . *NO      *YES, *NO

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TCPYTSK Copy Task or Subtask

Use this command to copy a task or subtask from one project to another. By default, this command creates a link between the original task and the new, copied task.

```
Copy Task/Subtask (TCPYTSK)

Type choices, press Enter.

From project . . . . . _____ Character value
From task . . . . . _____ Character value
From subtask . . . . . _____ Character value
To project . . . . . _____ Character value
To task . . . . . *NEXT Character value, *NEXT
To subtask . . . . . *NEXT Character value, *NEXT
Create Link Between Tasks . . . *YES *YES, *NO

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TCRTCMSCH Create Change Management Scheme

Use this command to create a change management scheme. (You must have TURNOVER® for iSeries v100 **System Defaults** authority to create change management schemes.) A change management scheme allows you to override change management methods (such as moving an object, copying an object, deleting an object, and so forth) for a user-defined object type. Once you create a change management scheme, you can update TURNOVER® for iSeries v100 global type code definitions to refer to it. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Create CM Scheme (TCRTCMSCH)

Type choices, press Enter.

Scheme . . . . . _____ Name
Description . . . . . _____
Default Program . . . . . *TURNOVER Name, *SCHEME, *NONE...
Library . . . . . *SCHEMELIB Name, *SCHEMELIB

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TCVTOBJTYP Convert Object Type

Use this command to convert an object from one type code to another; specifically, to convert RPG to RPGLE, or RPG to RPGMOD. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing ILE Programs (#60)*.

```

                                Convert Object Type (TCVTOBJTYP)

Type choices, press Enter.

Object . . . . . _____ Character value
From type . . . . . _____ Character value
To type . . . . . *SELECT Character value, *SELECT
Project/task reference . . . . . *WORKLIST Character value
Application . . . . . *WORKLIST Character value, *WORKLIST
Release . . . . . *WORKLIST Number, *WORKLIST
Version . . . . . *WORKLIST Number, *WORKLIST
Level . . . . . *PROD Number, *PROD
Programmer . . . . . *WORKLIST Character value

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TDLTAPPDFN Delete Application Definition

Use this command to delete an application definition. TURNOVER® for iSeries v100 deletes the application definition after it deletes all existing levels for the application. If TURNOVER® for iSeries v100 cannot delete one or more levels, either for security reasons or because forms or checkout records exist for the level, it does not delete the application definition. For more information, see *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Delete Application Definition (TDLTAPPDFN)

Type choices, press Enter.

Application . . . . . _____ Character value
Release . . . . . _____ Number
Version . . . . . _____ Number

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TDLTAPPLEV Delete Application Level

Use this command to delete a level from an application definition. To delete a level, you must have **System Defaults** authority to the level. Also, before you can delete a level, you must check in any items that are checked out for the level and you must purge any existing forms for the level, without retaining object history. For more information, see *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Delete Application Level (TDLTAPPLEV)

Type choices, press Enter.

Application . . . . . _____ Character value
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TDLTCMSCH Delete a Change Management Scheme

Use this command to delete a change management scheme. (You must have TURNOVER® for iSeries v100 **System Defaults** authority to delete CM schemes.) For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```

                                Delete CM Scheme (TDLTCMSCH)

Type choices, press Enter.

Scheme . . . . . > UTMENU           Name
Update type code definitions . . *NO      *NO, *YES

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TDSPOBJAUD Display Object Audit Info

Use this command to view information about an object as it is stored in TURNOVER® for iSeries v100's audit database.

```
10/18/04 14:52:27 Display Object Audit Information

Object . . . . . P165A          Source member . . . *NONE
Library . . . . . JFC
Object type . . . *PGM

Attribute      TurnOver Values  Actual Values
Object OWNER   QPGMR           SOMEOWNER
Object CHGDATE 1041014113411  1041014113534

F3=Exit  F12=Cancel

Bottom
```

TDSPOBJD Display Object Description

Use this command to view version information that TURNOVER® for iSeries v100 stores in an object's iSeries object description. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)*.

```
1/02/96 14:38:55 Display Object Description - TurnOver Your Company, Inc.

Object Information:
Object . . . . . : RPG001          Object version . . . . . : 003.000
Library . . . . . : MPPROD         Appl/Rel/Ver . . . . . : AP/00/00
Type . . . . . : *PGM
Object owner . . . . . : MARKPHIP
Creation Date/Time . . . . . : 12/29/95 15:40:20
Text . . . . . : Reads Record in CONTPF

Source Information:
Source file . . . . . : QRPGLSRC
Library . . . . . : MPPROD
Member . . . . . : RPG001
Attribute . . . . . : RPGLE
Source file date/time . . . . . : 12/29/95 15:39:36

TurnOver Information:
Created by form . . . . . : 1000028 Change RPG001 to Order Header File
Project/task reference . . . . . : MPTP0001 Change RPG001 to Order Header File
Type code . . . . . : RPGLE

F3=Exit  F5=*FULL  F6=View form  F8=*SERVICE  F9=View task  F12=Cancel

Bottom
```

TURNOVER® for iSeries v100 Commands

TIMERPT Project Timesheet Report

This command submits a job to report source checkout history, by application, by object or for a particular Project reference. See *Chapter 9: Working with Projects and Tasks* and *Chapter 10: TURNOVER® for iSeries v100 Reports* in the *TURNOVER® for iSeries v100 User Guide*.

```
Project Timesheet Report (TIMERPT)

Type choices, press Enter.

Project . . . . . *ALL          Char, *ALL
Task . . . . . *ALL          Char, *ALL
SubTask . . . . . *ALL       Char, *ALL
Status . . . . . *ALL       Code, *ALL
+ for more values
Resource (User-Id) . . . . . *ALL          Usrprf, *ALL
+ for more values
From date . . . . . 000000          Date, 000000
To date . . . . . 999999          Date, 999999
Print Selection Criteria . . . . . Y          Y, N
Only print summary info . . . . . N          Y, N

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TIMESHEET Enter Timesheet

This command presents the daily timesheet panel. See *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

```
Enter Timesheet (TIMESHEET)

Type choices, press Enter.

Resource . . . . . *CURRENT          Usrprf, *CURRENT
Date . . . . . 000000          000000=Today

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```


TURNOVER® for iSeries v100 Commands

TNEWRELOBJ New Related Object Rule

Use this command to change the rule that controls when and how new objects are created within a related application. For more about related applications, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)*. Also, for more information about the command, see the online Help.

```

                                New Related Object Rule (TNEWRELOBJ)

Type choices, press Enter.

Related Application . . . . . _____ Character value
Related Release . . . . . _____ Number
Related Version . . . . . _____ Number
New Related Object Rule . . . . . _____ *NONE, *DATA, *ALL

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TOPACK Pack Source Member

This command is used by TURNOVER® for iSeries v100 to pack archive source members. You can also use it and the **TOUNPACK** command to pack (compress) and unpack (decompress) your own source files. Please note that source must be unpacked before you attempt to compile it or have TURNOVER® for iSeries v100 promote it to production. The compression percent is displayed when the member is compressed. The member is compressed and saved as the same member name in the same source file as before it was packed.

```

                                Pack source member (TOPACK)

Type choices, press Enter.

Source file name . . . . . _____ Name
Library name . . . . . _____ *LIBL Name, *LIBL
Source member name . . . . . _____ Name

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TOPACKF

Pack a Source File

This command packs all the members of a source file. It uses the compress command. This command should be submitted to run in batch. For more information, see the **TOPACK** command.

```
                                Pack source file (TOPACKF)

Type choices, press Enter.

Source file name . . . . . _____ Name
Library name . . . . . _____ *LIBL Name, *LIBL

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TOUNPACK

Unpack Source Member

This command unpacks a source member that was packed (compressed) with the **TOPACK** command. For more information, see the **TOPACK** command.

TURNOVER® for iSeries v100 Commands

TPKGFORM

Package Form

This command creates a save file that TURNOVER® for iSeries v100 can use to distribute a form. The save file includes distributed source and objects as well as the TURNOVER® for iSeries v100 control files needed to create the form on another computer (using the **TUNPKGFORM** command). For more information, contact your UNICOM Systems, Inc. Sales Representative.

```
Package Form (TPKGFORM)

Type choices, press Enter.

Form number . . . . . _____ Number
Save file . . . . . _____ Name
Library . . . . . _____ Name
Clear save file . . . . . *NO *YES, *NO
Target Release . . . . . *DFT *DFT, *CURRENT, *PRV, V3R2M0..
Distribute source . . . . . *DFT *DFT, *YES, *NO
Distribute objects . . . . . *DFT *DFT, *YES, *NO
Distribute application defn. . . *NO *YES, *NO

Additional Parameters

Environment . . . . . *PRV *PRV, ENGLISH

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TPRTTSK

Print Task

This command prints a task using one of your project's pre-defined report masks. To choose a report mask from a list, type ***SELECT** in the *Report mask* field. If you have facsimile equipment attached to your iSeries network, you can design your report mask to produce "faxable" output for responding to users' requests. ***YES** in the *Check for fax number* field tells TURNOVER® for iSeries v100 to check the requestor file for the requestor's fax number. If there is not one, TURNOVER® for iSeries v100 returns an error and does not print the task.

```

                                     Print Task (TPRTTSK)

Type choices, press Enter.

Project/task/subtask . . . . . _____ Character value
Report mask . . . . . _____ Character value, *SELECT
Output queue . . . . . *MASK _____ Name, *MASK
  Library . . . . . *MASK _____ Name, *MASK, *LIBL
Check for fax number . . . . . *NO _____ *YES, *NO
Suppress hidden text . . . . . *YES _____ *YES, *NO

                                     Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TRGZARCF

Reorganize Source Archive File

Use this command to maintain archived source (versions of source older than the current version of source) on line and off line. In the application definition, you can indicate the qualified name of the source file to which source is to be archived. You can then periodically run this command to move archived members from one or more source archive files to another source archive file, based on selection parameters. (You can also access this command by selecting option **2** (*Work with source archive files*) on the Utility Menu, then selecting a file with option **2** on the *Work with Source Archive Files* panel.) For more information, see *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

```

                                Reorganize Source Archive File (TRGZARCF)

Type choices, press Enter.

Move members from file . . . . . *ALL      Name, *ALL
   Library . . . . . *ALL      Name, *ALL
Move members to file . . . . .           Name
   Library . . . . .           Name
Move members archived before . . *ALL      Date, *ALL
Move versions greater than . . . *ALL      Number, *ALL

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TRMTCFGWIZ Run the Remote Configuration Wizard

Use this command to run the Remote Configuration Wizard to send application or system definitions to remote systems. For more information, see the online Help and the *Remote Configuration Wizard* topic in *Chapter 11: Distributing Changes to Production Computers* of the *TURNOVER® for iSeries v100 User Guide*.

```
12/01/98                Remote Configuration Wizard                Your Company, Inc.
12:28:05                Panel 1 of 5                               SLS

Welcome to the TurnOver Remote Configuration Wizard. The Wizard is designed
to simplify the process of sending TurnOver application and system definitions
to the remote system. You will step through a series of panels that will
gather information about what you need to send to your remote systems.

On each panel, after responding to the necessary prompts, you can press ENTER
to continue to the next panel, or press F12 to go back to the previous panel.
You can press F3 at any time, to end the process.

Press ENTER to continue.

ENTER=Next Panel      F3=Exit Wizard
```

TRPTCON Report Conflicts

Use this command to produce a report of related application conflicts, including an audit history of conflict resolutions. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)* and the online Help.

```
Report Conflicts (TRPTCON)

Type choices, press Enter.

Object . . . . . *ALL _____ Name, *ALL
Base library . . . . . *ALL _____ Name, *ALL
Type code . . . . . *ALL _____ Character value
Include only objects on form . . *NO _____ Number, *NO
Base application . . . . . *ALL _____ Character value
Base release . . . . . *ALL _____ Number, *ALL
Base version . . . . . *ALL _____ Number, *ALL
Base level . . . . . *ALL _____ Number, *ALL
Conflict type . . . . . *ALL _____ *ALL, *CHKOUT, *FORM
Conflict from date . . . . . 000000 _____ Date, 000000
Conflict to date . . . . . 999999 _____ Date, 999999
Base programmer . . . . . *ALL _____ Name, *ALL
Base reference . . . . . *ALL _____ Name, *ALL
Related library . . . . . *ALL _____ Name, *ALL
Related application . . . . . *ALL _____ Character value
Related release . . . . . *ALL _____ Number, *ALL

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

Page down
for more fields.

More...

TURNOVER® for iSeries v100 Commands

TRSTCMSCH Restore Change Management Scheme

Use this command to restore a change management scheme definition that was previously saved, and optionally restore its method programs and resource library (containing any additional objects required by the method programs), from a save file. (The save file must have been created with the **TSAVCMSCH** command.) For more information, see the **TURNOVER®** for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Restore CM Scheme (TRSTCMSCH)

Type choices, press Enter.

Save file . . . . . _____ Name
Library . . . . . *LIBL _____ Name, *LIBL
Restore to scheme . . . . . *SAVSCHEME _____ Name, *SAVSCHEME
Replace existing scheme . . . . . *NO _____ *NO, *YES
Restore method programs . . . . . *YES _____ *YES, *NO
RSTLIB for method programs . . . . . *SCHEME _____ Name, *SCHEME
Restore resource library . . . . . *YES _____ *YES, *NO
RSTLIB for resource library . . . . . *SAVLIB _____ Name, *SAVLIB

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TRTNOBJDTA Set RTNOBJDTA Parameter

Use this command in a change management method program (CL program only) to parse the return data. For more information, see the **TURNOVER®** for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Set RTNOBJDTA Parameter (TRTNOBJDTA)

Type choices, press Enter.

RTNOBJDTA in . . . . . _____
_____
_____
_____
_____
_____
_____
Data type . . . . . _____ *TEXT, *OWNER, *RTNLIB...
Value . . . . . *NULL _____
CL variable for returned value _____ Character value

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TRTVCMPARM Retrieve CM Method Parameter

Use this command in a change management method program (CL program only) to parse the incoming *Object data* parameter into program variables. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Retrieve CM Method Parameter (TRTVCMPARM)

Type choices, press Enter.

Object data . . . . . _____
_____
_____
_____

Parameter . . . . . _____ *FORM, *LINE, *TYPCD...
CL variable for returned value _____ Character value

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TRUNCMMTH Run CM Method

Use this command to execute a CM method from within the method program for another CM method. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Run CM Method (TRUNCMMTH)

Type choices, press Enter.

Scheme . . . . . _____ Name
Method . . . . . _____ *ARCHIVE, *BROWSE, *CHGOBJ, ...
Object data . . . . . _____
_____
_____
_____

Return error Y/N flag . . . . . _____ Character value
Return data . . . . . _____ Character value

                                                    Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```


| | |
|-----------------|---------------------------------|
| TSAVARCF | Save Source Archive File |
|-----------------|---------------------------------|

Use this command to maintain archived source (versions of source older than the current version of source) on line and off line.

```

                                Save Source Archive File (TSAVARCF)

Type choices, press Enter.

Source archive file . . . . . *DEFAULT      Name, *DEFAULT
Library name . . . . . *LIBL              Name, *LIBL
Volume . . . . . _____              Character value
Device . . . . . _____              Character value

                                Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

In the application definition, you can indicate the qualified name of the source file to which source is to be archived. You can then periodically run this command to save source off line, and at the same time update TURNOVER® for iSeries v100's archive history to keep track of which archived versions have been saved to which media volumes.

You can also access this command by selecting option **2** (*Work with source archive files*) on the Utility Menu, then selecting a file with option **3**=**Save** on the *Work with Source Archive Files* panel. For more information, see *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

TSAVCMSCHE Save Change Management Scheme

Use this command to save a change management scheme definition, and optionally save its method programs and resource library, to a save file. (The resource library contains any additional objects required by the method programs.) For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
Save CM Scheme (TSAVCMSCHE)

Type choices, press Enter.

Scheme . . . . . > UTMENU      Name
Save method programs . . . . . *YES      *YES, *NO
Save resource library . . . . . *NONE      Name, *NONE
Save file . . . . . _____      Name
  Library . . . . . _____      *LIBL      Name, *LIBL
Target release . . . . . *CURRENT      *CURRENT, *PRV, VnRnMn ...

                                           Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TSAVIFSARC Save IFS Archive Directory

Use this command to save an IFS archive subdirectory and, optionally, to clear the subdirectory after it's saved. For more information, see the online Help and the *Saving an IFS Archive Directory* topic in *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

```
Save IFS Archive Directory (TSAVIFSARC)

Type choices, press Enter.

Volume . . . . . _____      Character value
Device . . . . . _____      Character value
Clear directory after save . . . . . *YES      *YES, *NO

                                           Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TSETAPPOBJ Set Application Object

Use this command to set the initial version number for all objects in an application to a value you specify. To learn about other helpful features associated with this command, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)*.

```
Set Object Version Information (TSETAPPOBJ)

Type choices, press Enter.

Application . . . . . _____ Character value
Release . . . . . _____ Number
Version . . . . . _____ Number
Level . . . . . _____ Number
Major Version number . . . . . _____ Number
Minor Version number . . . . . _____ Number
Objects to process . . . . . *NEW *ALL, *NEW
Stamp object version . . . . . *YES *YES, *NO
Stamp last form . . . . . *NO *YES, *NO
Stamp last reference . . . . . *NO *YES, *NO
Stamp last type code . . . . . *NO *YES, *NO

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TSETOBJVER Set Object Version

Use this command to set the initial version information for the objects in an application, processing objects by name, library, and type. (See also TSETAPPOBJ above.) For more information about this command, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)*.

```
Set Object Version Information (TSETOBJVER)

Type choices, press Enter.

Object Name . . . . . _____ Name, *ALL
Library Name . . . . . _____ Name
Object Type . . . . . _____ Name, *ALL
Major Version number . . . . . _____ Number
Minor Version number . . . . . _____ Number
Application . . . . . _____ Character value
Application release . . . . . _____ Number
Application version . . . . . _____ Number
Objects to process . . . . . *NEW *ALL, *NEW
Stamp object version . . . . . *YES *YES, *NO
Stamp last form . . . . . *NO *YES, *NO
Stamp last reference . . . . . *NO *YES, *NO
Stamp last type code . . . . . *NO *YES, *NO

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

TSETRSTDLY Set Restore Delay Defaults

Use this command to set retry and delay times for the TURNOVER® for iSeries v100 form receive process, when a form is received on a remote computer.

```
Set Restore Delay Defaults (TSETRSTDLY)

Type choices, press Enter.

Number of retries . . . . . 2          0 - 9
Delay time between retries . . . 005     Seconds
Action to perform after retries . *END   *END, *MSG
Message queue . . . . . QSYSOPR       Name, *SAME
Library . . . . . *LIBL             Name, *LIBL, *SAME

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

Bottom
```

TSTRESCQ Start Escalation Queue Monitoring

This command starts the escalation queue monitor or changes the monitoring time interval.

```
Start Escalation Queue Monitor (TSTRESCQ)

Type choices, press Enter.

Wake-up interval (seconds) . . *DFT     Number, *DFT

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

Bottom
```

This command must be submitted using the **SBMJOB** command; it cannot be run interactively. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Setting Up TURNOVER® for iSeries v100 Autostart jobs (#25)*.

TURNOVER® for iSeries v100 Commands

TUNPKGFORM Unpackage Form

This command is used by TURNOVER® for iSeries v100 to receive and, optionally, run a TURNOVER® for iSeries v100 form from a save file that was created using the **TPKGFORM** command. For more information, contact your UNICOM Systems, Inc. Sales Coordinator.

```

                                Unpackage Form (TUNPKGFORM)

Type choices, press Enter.

Save file . . . . . _____ Name
Library . . . . . _____ Name
Packaged form number . . . . . *PKG _____ Number, *PKG
Unpackaged form number . . . . . *PKG _____ *PKG, *NEXT
Update application definition . . . . . *NO _____ *YES, *NO
Run form . . . . . *INTER _____ *INTER, *BATCH, *DFT, *NO

                                Additional Parameters

Environment . . . . . *PKG _____ *PKG, *PRV, Environment name

                                                                Bottom
F3=Exit    F4=Prompt    F5=Refresh    F12=Cancel    F13=How to use this display
F24=More keys
```

TUPDHLPTSK Update Related Helpdesk Tasks

This command, which you'll typically use in an escalation table, updates the Helpdesk tasks associated with a Working task. This command is triggered when the Working task assumes a status of ASSIGNED or DONE.

```

                                Update Related Helpdesk Tasks (TUPDHLPTSK)

Type choices, press Enter.

*WORKING Task . . . . . _____ Character value
Helpdesk Task(s) to Update . . . . . *ALL _____ Character value, *ALL, *FIRST
Update Task Details . . . . . *YES _____ *YES, *NO
Process Escalation Entries . . . . . *YES _____ *YES, *NO

                                                                Bottom
F3=Exit    F4=Prompt    F5=Refresh    F12=Cancel    F13=How to use this display
F24=More keys
```

For more information, see the *Escalation* topic (specifically, *Working with escalation table commands*) in *Chapter 9: Working with Projects and Tasks* of the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

TURNOVER

TURNOVER® for iSeries v100 Main Menu Command

This command accesses the TURNOVER® for iSeries v100 Main Menu or an option on the TURNOVER® for iSeries v100 Main Menu from a command line. You must be enrolled in TURNOVER® for iSeries v100 to use this command (see page 1).

TVFYOBJAUD

Verify Object Audit Info

This command is for use within an exit or other program to confirm that an object's creation information matches that of its source. Your program should monitor for abnormal termination messages.

TWRKCMSCH

Work with Change Management Schemes

Use this command to view all change management schemes that have been defined to TURNOVER® for iSeries v100. A change management scheme allows you to override change management methods (such as moving an object, copying an object, deleting an object, and so forth) for a user-defined object type. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing User-Defined Object Types (#59)*.

```
5/30/01          Work with Change Management Schemes      Your Company, Inc.
08:05:04                                               YOURSYS

2=Change  3=Copy  4=Delete  5=Methods  7=Usage  9=Save

  Scheme      Description
  _ UTBIO      Employee Biography Scheme
  _ UTMENU     Menu System Scheme

                                                    Bottom

F3=Exit  F6=Add  F8=Restore  F12=Cancel  F21=System command
```

TURNOVER® for iSeries v100 Commands

TWRKCON Work with Conflicts

Use this command to view a list of related application conflict changes that have been made. This information is stored in the Related Application Conflict file. For more information, see the TURNOVER® for iSeries v100 Supplement entitled *Managing Multiple Versions (#63)* and the online Help.

```

Work with Conflicts (TWRKCON)

Type choices, press Enter.

Object . . . . . *ALL      *ALL, Object name
Base library . . . . . *ALL      *ALL, Library name
Attribute . . . . . *ALL      *ALL, TurnOver type code
Conflict type . . . . . *ALL      *ALL, *CHKOUT, *FORM
Base application . . . . . *ALL      *ALL, Application
Base release . . . . . *ALL      *ALL, Number
Base version . . . . . *ALL      *ALL, Number
Base level . . . . . *ALL      *ALL, Number
User . . . . . *ALL      *ALL, Usrprf
Project/task reference . . . . . *ALL      *ALL, Project/task
Form number . . . . . *ALL      *ALL, Form number
Related library . . . . . *ALL      *ALL, Library name
Related application . . . . . *ALL      *ALL, Application
Related release . . . . . *ALL      *ALL, Number
Related version . . . . . *ALL      *ALL, Number
Related level . . . . . *ALL      *ALL, Number

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
    
```

Page down
for more fields.

More...

TWRKLIC Work with Licenses

Use this command to check the status of each TURNOVER® for iSeries v100 product and to enter new authorization codes. For more information, see *Chapter 5: Additional Installation Topics* (specifically the *Applying Authorization Codes* section) in the *Getting Started with TURNOVER® for iSeries v100* guide.

```

16:00:58          Work with Licenses
1/12/00

Serial Number . . . . . 103NK7M      Press F1 to see help and
Model . . . . . 170                  additional information
Processor Group . . . . . P10        regarding license codes.
Feature Code . . . . . 2292

1=Enter License Code

  Product          Expires  Users
- TurnOver Development  Permanent Unlimited
- TurnOver C/S Host      Permanent Unlimited
- TurnOver C/S Helpdesk  Permanent 100
- TurnOver C/S Projects  Permanent Unlimited
- TurnOver C/S Helpdesk Lite Permanent 200
- LanTurn Interface     No Code
- MS Project Interface   Invalid  Unlimited
- TurnStyle Interface    Permanent 4
- Over:2E Interface     No Code
- ProTurn Interface     No Code

F3=Exit  F5=Refresh  F12=Cancel  F21=Command line
    
```

Bottom

TURNOVER® for iSeries v100 Commands

TWRKTSK Work with Tasks

There is one parameter (*Project*) for this command. This command provides an alternate path to the *Work with Projects* and *Work with Tasks* panels. See *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

VIEWDFTS View Defaults

There are no parameters for this command. This command provides another way to view application definitions. See *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

VIEWGLOBE View Global Defaults

There are no parameters for this command. This command provides an alternate path to the *View Global TURNOVER® for iSeries v100 Defaults* panel.

VIEWPTFHST View PTF History

There are no parameters for this command. It displays the history of TURNOVER® for iSeries v100 system program temporary fixes applied to your system.

WDDYNUPD Wisedesk Dynamic Update

Use this command to control dynamic maintenance of help trees on your system. This command creates a data queue (if none exists) and starts, stops, or delays a job that monitors the data queue. For more information, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

```
Wisedesk Dynamic Update (WDDYNUPD)

Type choices, press Enter.

Action code . . . . . *START, *STOP, *DLYJOB...
Data queue . . . . . WDDYNUPD Character value
Data queue library . . . . . *LIBL Character value

Bottom
F3=Exit F4=Prompt F5=Refresh F12=Cancel F13=How to use this display
F24=More keys
```


TURNOVER® for iSeries v100 Commands

WORKTASK Work with Entered Problems/Requests

There are no parameters for this command. This accesses the Problem/Request review panels, normally used by a project coordinator. For more information, see *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

WRKAPPDFN Work with Application Definition

This command is the same as selecting Main Menu option 1 to work with application definitions. By entering an option, you can go directly into a specific application definition panel. For more information, see the *TURNOVER® for iSeries v100 Application Planning Guide* and *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

```
Work w/ Application Definition (WRKAPPDFN)

Type choices, press Enter.

Application . . . . . *SLT      *SLT, Name
Release . . . . .      _      Number
Version . . . . .      _      Number
Level . . . . .      _      Number
Option . . . . . *NONE    *NONE, 1, 2, 3, 4, 5, 6, 7...
System . . . . . *LOCAL   *LOCAL, Name

                                           Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

WRKAPPGRP Work with Approval Groups

There is one parameter (*Approval group*) for this command. This command provides an alternate path to the *Work with Approval Group Objects* panel where you can view and maintain approval groups. (You can also access this panel by selecting, for an application, the *Approval list* application default, then pressing F9 (*Add group*) on the *Approval List* panel.) For more information, see the *TURNOVER® for iSeries v100 Application Planning Guide* and *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

WRKAPPLST Work with Approval Lists

There is one parameter (*Approval list*) for this command. This command provides an alternate path to the *Work with Approval List Objects* panel where you can view and maintain approval lists. (You can also access this panel by selecting, for an application, the *Approval list* application default, then pressing **F4** on the *Approval list name* field on the *Approval List* panel.) For more information, see the *TURNOVER® for iSeries v100 Application Planning Guide* and *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

WRKCATSTR Work with Strings for Category

Use this command to work with search strings for a help tree category. This is the same as selecting a category or subcategory with option **7** on the *Work with Categories* panel. For more information about help trees and search strings, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

```
Work with Cat. Search Strings (WRKCATSTR)

Type choices, press Enter.

Tree . . . . . _____ Name
Path . . . . . _____
_____
_____

Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

WRKCATTSK Work with Tasks for Category

Use this command to work with the tasks associated with a help tree category. This is the same as selecting a category or subcategory with option **12** on the *Work with Categories* panel.

```
Work with Category Tasks (WRKCATTSK)

Type choices, press Enter.

Tree . . . . . _____ Name
Path . . . . . _____
_____
_____

Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

WRKDSTSYS Work with System Definitions

There are no parameters for this command. This command provides an alternate path to the *Maintain System Definitions* panel. See *Chapter 11: Distributing Changes to Production Computers* in the *TURNOVER® for iSeries v100 User Guide*.

WRKESCQ Work with Escalation Queue

There are no parameters for this command. For more about the *Escalation queue*, see *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

WRKFORMLOG Work with Form Log

This command is available as option 4 on the TURNOVER® for iSeries v100 Distribution Menu. For more information, see *Chapter 11: Distributing Changes to Production Computers* in the *TURNOVER® for iSeries v100 User Guide*.

```
Work with Form Log (WRKFORMLOG)

Type choices, press Enter.

Form number . . . . . *LAST      Number, *LAST
System number . . . . . *PRV      Number, *PRV, *ALL
Function . . . . . *PRV          *PRV, *ALL, *CREATE, *COPY...
      + for more values

Time period:
Beginning time . . . . . *PRV      Time, *PRV, *AVAIL
Beginning date . . . . . *PRV      Date, *PRV, *AVAIL
Ending time . . . . . *PRV        Time, *PRV, *AVAIL
Ending date . . . . . *PRV        Date, *PRV, *AVAIL

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

WRKGRPFOR Work with Form Group Forms

Use this command to specify a form group name (TonnnnnnnG) and work with all forms in that form group or to specify a form number and work with all forms that are in the same form group as that form. For more information, see *Chapter 7: Submitting a TURNOVER® for iSeries v100 Form to Run* in the *TURNOVER® for iSeries v100 User Guide*.

```
Work with Form Group Forms (WRKGRPFOR)

Type choices, press Enter.

Form group . . . . . *FORM      Form group, *FORM
Form . . . . . *GROUP        Number, *GROUP

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

TURNOVER® for iSeries v100 Commands

WRKHLPTREE Work with Help Trees

This command is available through option **16** within HELPDESK and as **F16** within both WORKTASK's task review panel and TURNOVER® for iSeries v100 Project's *Work with Tasks* panel, as well as from any command line within TURNOVER® for iSeries v100. For more information, see the *Wisedesk* topic in *Chapter 9: Working with Projects and Tasks* in the *TURNOVER® for iSeries v100 User Guide*.

WRKOBJREF Work with Object References (X-Ref)

This command is available as option **33** on the Checkout/Check-in Menu, and as option **15** on the *Programmer Worklist*.

```
Work with Object References (WRKOBJREF)

Type choices, press Enter.

Object Name . . . . . _____ Name
Library Name . . . . . _____ Name
Type code . . . . . _____ AAUDIT, ABPGM, ADMDL, ADPGM...
X-Ref Table Name . . . . . _____ APDEMO, DEFAULT, J52XREF, L...
Output . . . . . *_____ * , *PRINT

                                                                 Bottom
F3=Exit   F4=Prompt   F5=Refresh   F12=Cancel   F13=How to use this display
F24=More keys
```

WRKPWMDFT Global PWM Session Defaults

There are no parameters for this command. This command provides an alternate path to the *Global Worklist Session Defaults* panel. (You can also access this panel by selecting option **8** (*Utility menu*) on the TURNOVER® for iSeries v100 Main Menu, then selecting option **12** on the Utility Menu. For more information, see *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

TURNOVER® for iSeries v100 Commands

WRKRCVJOB Work with Receive Form Jobs

Use this command from a command line, or as a user option, to locate all jobs (RCVTONETF or TOAUTORCV) associated with receiving a distributed TURNOVER® for iSeries v100 form.

```
9/15/95 14:25:46          Work with Receive Form Jobs          Your Company Inc.

Form . . . . . 105789
Description . . . Work with Receive Form Jobs command

1=Work with job

  Job          User          Number  Status
- RCVTONETF   TURNOVER   190921  *FIN
- TOAUTORCV   TURNOVER   190922  *OUTQ

F3=Exit  F5=Refresh  F12=Cancel  F21=System command

Bottom
```

If a form has been redistributed, you will see more than one RCVTONETF and TOAUTORCV job for the form.

WRKRMTAPP Work with Remote Applications

There are no parameters for this command. This command provides an alternate path to the *Work with Remote Application Definitions* panel. (You can also access this panel by selecting option 11 (*Distribution menu*) on the TURNOVER® for iSeries v100 Main Menu, then selecting option 5 on the TURNOVER® for iSeries v100 Distribution Menu. For more information about distributing, see *Chapter 11: Distributing Changes to Production Computers* in the *TURNOVER® for iSeries v100 User Guide*.

WRKTODATA Work with *DATA Object Types

There are no parameters for this command. This accesses the *Work with *DATA Files* panel. For more information, see the section entitled *Working with *DATA Definitions* in *Chapter 5: Checking Out/Checking In Source* of the *TURNOVER® for iSeries v100 User Guide*.

WRKTOENV Work with TURNOVER® Environments

There are no parameters for this command. This command accesses TURNOVER® for iSeries v100's environment control file. For more about TURNOVER® for iSeries v100 environments, see *Chapter 5: Additional Installation Topics* in the *Getting Started with TURNOVER® for iSeries v100* guide as well as the TURNOVER® for iSeries v100 Supplement entitled *Setting Up Additional TURNOVER® for iSeries v100 Environments (#32)*.

TURNOVER® for iSeries v100 Commands

| | |
|------------------|--|
| WRKTOEXIT | Work with TURNOVER® Exit Programs |
|------------------|--|

There are no parameters for this command. Alternate path: select Main Menu **8** and then option **7**. See *Chapter 8: Utility Menu* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|-----------------|---------------------------------------|
| WRKTOLLO | Work with Library List Objects |
|-----------------|---------------------------------------|

There is one parameter. This provides direct access to the *Work with TURNOVER® for iSeries v100 Library List Objects* panel. See the *Library lists* topic in *Chapter 1: Working with Application Definitions* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|-----------------|---|
| WRKTOTYP | Work with TURNOVER® Object Type File |
|-----------------|---|

There are no parameters for this command. This command provides an alternate path to the *Work with Object Type File* panel (Utility Menu option **4**).

| | |
|------------------|-----------------------------|
| WRKTSKFOR | Work with Task Forms |
|------------------|-----------------------------|

There is one parameter (*Project task reference*) for this command. This command provides an alternate path to the *Work with TURNOVER® for iSeries v100 Forms for Task* panel. (You can also access this panel by selecting, on the *Work with Tasks* panel, a task with option **16=Forms**.) See *Chapter 6: Working with TURNOVER® for iSeries v100 Forms* in the *TURNOVER® for iSeries v100 User Guide*.

| | |
|------------------|----------------------------------|
| WRKUSRREF | Work with User References |
|------------------|----------------------------------|

There is one parameter (*X-Ref Table Name*) for this command. This command provides a path to the *Work with User Defined References* panel where you can add your own references to a cross-reference table.

If you have any questions about the information in this document, please contact a UNICOM Systems, Inc. Technical Support Representative by phone, fax, or email at the locations shown at the beginning of this document.